UNIVERSITY OF CAMBRIDGE INTERNATIONAL EXAMINATIONS GCE Advanced Subsidiary Level and GCE Advanced Level

## www.papacambridge.com MARK SCHEME for the October/November 2010 question paper

## for the guidance of teachers

## 9691 COMPUTING

9691/12

Paper 1 (Written Paper), maximum raw mark 90

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes must be read in conjunction with the question papers and the report on the examination.

CIE will not enter into discussions or correspondence in connection with these mark schemes.

CIE is publishing the mark schemes for the October/November 2010 question papers for most IGCSE, GCE Advanced Level and Advanced Subsidiary Level syllabuses and some Ordinary Level syllabuses.

Pa	age 2	Mark Scheme: Teachers' version Syllabus	er
		GCE A/AS LEVEL – October/November 2010 9691	1
har -Me -pro -Tc -Pr exa -se -HC -Au -all -int	rdwar emor ovide covide covide ample cond CI/ex utoma low c terrup	Mark Scheme: Teachers' version         Syllabus           GCE A/AS LEVEL – October/November 2010         9691           trol the hardware of the computer/to ensure that the hardware can communic         9691           trol the hardware of the computer/to ensure that the hardware can communic         9691           y management/to ensure efficient use of memory         a platform on which to run/load software/provide translators for software.           trol access to the computer/user IDs and passwords/security and privacy of system         utility programs/to aid with housekeeping, maintenance/example utility/description           example of utility/description         ample/description e.g. WIMP interface           atic backup/description of a backup routine/incremental backup         backup           omputer to be used in different ways/description of a type of OS e.g. network/multion         thandling/example of a type of interrupt with action required	
(Ma	ax 2 j	per -, max 4-, max 8)	[8]
(a)	(i)	-The code produced by the programmer -in high-level language.	[2]
	(ii)	-Source code is in human understandable language/the computer cannot underst commands. -The translator produces binary/machine code/executable form which the compu- understand. (Accept machine readable if clear that candidate is referring to translated versio code.)	uter can
(b)	(i)	-Error in the grammar (language rules) of the program (not just by example)	[0]
(c)		<ul> <li>-Instruction to perform inappropriate arithmetic (accept examples)</li> <li>-The testing of logical paths through the code</li> <li>-All logical paths</li> <li>-tests structure and logic of program</li> <li>-use of a dry run</li> </ul>	[2]
	(ii)	(1 per -, max 2) -Testing by members of software house	[2]
		-Version may not be finished -Testers have knowledge of programming/software. (1 per -, max 2)	[2]
(a)	(i)	-Text/alpha/string/alphanumeric (not character) -These are sets of characters, not numbers/no calculation involved with them (second mark depends on the first)	[2]
	(ii)	-Integer/byte -Must be whole number	[2]

Page	:3		e: Teachers' version	Syllabus	er
		GCE A/AS LEVEL	– October/November 2010	9691 23	
۲-۴ F-F	Records Fields (in	dividual pieces of data	dents) comprise… ingle student) comprise… a e.g. home telephone numbe am <i>(only award one mark for th</i>	,	mbilds
-w -c Ad	which has can be in		experts and		[2]
-w -T Ao kr	which the These rul ccept pe	oints made in terms e base to get diagnosi	o adhere to knowledge to provide results ( s of this example e.g. sym		ied to [2]
-Each -Barco -Item o -Numb -Comp -If < re -no ou	item is k ode read code fou ber in sh parison r eorder le	control software bar coded (on exit from shop/en ind on item file op decremented/incre nade with reorder leve vel then order placed g order yet made	emented		[6]
Ca So No	oftware: letwork C	or Wireless network	card/Server/wireless access p work versions of software.	point	[3]
-S 		ts: /er/Switch at centre al shown/Central stora	ıge		[3]
-N -e	Number of	e has extra parity bit of ones in byte (+ parit d or even (dependent a transmitted the parity	on parity) (reject: byte is odd/	-	

Page 4	Mark Scheme: Teachers' version	Syllabus S	er
	GCE A/AS LEVEL – October/November 2010	9691	°C.
.g.			ar ar an a
= M = New	T = MFour = 0		(1) (1) (1)
	1900 TO 2009		(1)
READ M LET T =	lean T + Mean		(1) (1)
IEXT			( ' )
ET M = T/1 <sup>-</sup>	10		(1)
REPEAT	ChosenYear		(1)
	senYear >= 1900) AND (ChosenYear <= 2006)		(1)
	ChosenYear TO ChosenYear + 3		(1)
READ M	lean vT = NewT + Mean		(1) (1)
IEXT			(')
ET MFour =	· NewT/4		(1)
F MFour > N		,	
	UTPUT "HOT" UTPUT "NORMAL"	}	(1)
NDIF		,	( ' )
lark Points:			
Initialise vari Sensible var	iables riable names used		
Loop to read	d all means		
with correct			
Mean read ii Running tota			
	of mean of summer means outside loop		
Input of year	r		
	four means		
with correct Mean read a			
	and cumulative total kept ears calculated outside loop		
	with mean+4		
	les with sensible conditions		
	one of the inputs		
1 per -, max	10)		[10

			4444	
	Page 5	5	Mark Scheme: Teachers' version Syllabus	er
			GCE A/AS LEVEL – October/November 2010 9691	
	(i)		: See first hand the system operating/may spot problems actual users do n People do not act naturally if they are being watched/only see a snapshot.	ambric
	(ii)		Mark Scheme: Teachers' version       Syllabus         GCE A/AS LEVEL – October/November 2010       9691         : See first hand the system operating/may spot problems actual users do n         People do not act naturally if they are being watched/only see a snapshot.         . Detail can be explored/direction of enquiries can be altered         Very time consuming         Shows how data is collected/shows data that needs to be collected	[2]
	(iii)	infor Dis.	. Shows how data is collected/shows data that needs to be collected mation that needs to be output. Documentation often difficult for an outsider to understand/Privacy evance of files	, 0110110
)	-pr	obabl	ue of measuring by callipers y by shining laser light at metal and measuring shadows produced. sensible method)	[2]
	(b) (i)		nge check <i>(or a description of range check)</i> ween a maximum which will fit in machine/minimum must be greater than f th.	inished [2]
	(ii)	-Cor -Visi	ue input twice mputer compares two values, if different, then error ual check erator looks at value typed in as it appears on screen and checks it is correct.	[4]
	-Printed -On scr -Lights (2 per -	d repo reen ir or sou , max	to show temperatures of machines orts/hard copy/e.g. to show details of the day's output mage/e.g. showing progress of jobs on each machine und/e.g. to show alarm for machine, or a machine requiring attention. 3 -, max 6)	[6]
1	-Pr -e.( -bu e.g	g. to a inter g. to r izzer i. to si	allow operator to see immediate confirmation of inputs (when changing parame etain permanent copy for records gnify that change is accepted/not passed validation procedures max 2 pairs, max 4)	eters) [4]
	-Ar -Ins	eas o structi	es a hard copy form f screen reserved for specific inputs ions can be supplied uttons/drop down lists	
	-Inj -Da	put ca ata to	ot allow any necessary data to be missed on be self-validating be input will be standard dependent on machine. max 3 of first four points, max 4)	[4]

